

FUSION LR-CC



LR-CC Soundbar System

Though more and more people continue to hop on the soundbar train, some are being left at the station as they simply cannot fit a soundbar beneath their television. Whether it is due to their television being mounted above a fireplace mantel or in the confines of a restrictive entertainment center, some will think that achieving a full LCR surround sound experience may have to be sacrificed to make an external soundbar solution work. Just like an LCR soundbar, the Fusion LR-CC offers all three surround sound channels (i.e., left, center and right) in a two-part system that mounts on the sides of the television. While the speakers have dedicated left and right channels, it also incorporates a split center channel design allowing for full LCR audio support.

SPECS DESCRIPTION	SPECS
System Design	Sealed Soundbar
Woofer	(3) D Series 3.3" / 4.5"
Tweeter	(2) 1" Vifa BC Neodymium Silk Dome
Power- Min/ Max – RMS	20-200 W (3.3") 20-400 W (4.5")
Frequency Response	80 Hz- 20 kHz (3.3") 60 Hz – 20 kHz (4.5")
Impedance	4 ohms LR (WTW) / 8 ohms C (TW)
Sensitivity	88 dB (3.3") / 89 dB (4.5")
Dimensions (3.3")	4.5" w x 2.8" d x custom" h
Dimensions (4.5")	5.06" w x 3" d x custom" h